



## **SPECIFICATIONS**

| Model Name               | A520M-A PRO   |
|--------------------------|---|
| CPU Support              | Support 3rd Gen AMD Ryzen <sup>™</sup> Desktop Processors and AMD |
|                          | Ryzen <sup>™</sup> 4000 G-Series Desktop Processors               |
| CPU Socket               | AMD Socket AM4  |
| Chipset                  | AMD A520 Chipset  |
| Graphics                 | 1x PCI-E 3.0 x16 slot   |
| Interface                |   |
| <b>Display Interface</b> | HDMI, DVI-D - Requires Processor Graphics                         |
| Memory Support           | 2 DIMMs, Dual Channel DDR4-4600MHz (OC)                           |
| <b>Expansion Slots</b>   | 1x PCI-E 3.0 x1 slot  |
| Storage                  | 1x M.2 Gen3 x4 slot, 4x SATA 6Gb/s ports                          |
| USB ports                | 6x USB 3.2 Gen 1 5Gbps (Type-A) + 6x USB 2.0                      |
| LAN                      | Realtek® RTL8111H Gigabit LAN                                     |
| Audio                    | 8-Channel (7.1) HD Audio with Audio Boost                         |

## **FEATURES**



## **EZ Debug LED**

Easiest way to troubleshoot.



#### **Audio Boost**

Reward your ears with studio grade sound quality for the most immersive audio experience.



### Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.



### **Core Boost**

With premium layout and fully digital power design to support more cores and provide better performance.



### 2oz Thickened Copper PCB


An enhanced PCB design improves heat dissipation and performance reliability.



### **DDR4 Boost**

Advanced technology to deliver pure data signals for the best gaming performance and stability.

# **CONNECTIONS**



- 1. LAN port
- 3. DVI-D
- 5. USB 3.2 Gen 1 5Gbps Type-A
- 7. USB 2.0 Ports
- 2. HDMI
- 4. Keyboard / Mouse
- 6. USB 3.2 Gen 1 5Gbps Type-A
- 8. Audio Connectors